

# SmartMOD

---



6th Gen Intel® Core™ Processor Ultra-compact Fanless Box Computer

## Features

- Ultra-compact size: 238 x 129 x 63.7mm
- 6th Gen Intel® Core™ Processor, Skylake platform
- Wide-Range DC voltage input: 9V~32V
- Fanless system, aluminum alloy structure
- 6x RJ45 GbE Ethernet
- 1x RS-232/422/485, 5x RS-232
- Multi-Display: 1x HDMI/VGA and 1x DP
- 2x Mini-PCle with SIM socket (PCle + USB + USIM)
- 1x mSATA socket, 1x 2.5" drive bay for HDD/SSD
- 16-bit programmable GPIO

## Headquarter

10F-3, No. 270, Sec. 4,  
Chung Hsiao E. Rd.,  
Taipei, 10694, Taiwan

T +886 2 2751-7192  
E-mail: [info@efco.com.tw](mailto:info@efco.com.tw)

## EMEA

T +49-991-2009298-0  
E-mail: [info@efcotec.com](mailto:info@efcotec.com)

## America

T +1-760-827-8600  
E-mail: [sales-us@efcotec.com](mailto:sales-us@efcotec.com)

**EFCO**  
EverFine Group

Model	Description
<b>U6-561</b>	<p>U6-500 Fanless Box PC</p> <p>CPU: Intel® Celeron® 3955U (2x 2.0GHz, 2MB L2Cache, 15W)</p> <p>Memory: DDR4 2x SODIMM</p> <p>Front Side</p> <ul style="list-style-type: none"><li>• 1 x HDMI</li><li>• 1 x Display Port</li><li>• 1 x VGA</li><li>• 4 x USB 3.0/2.0</li><li>• 6 x 10/100/1000Mbps Ethernet</li><li>• 1 x GPIO (4/4bit)</li></ul> <p>Rear Side</p> <ul style="list-style-type: none"><li>• 1 x Audio (Line-out/ MIC-in)</li><li>• 1 x VHDCI (8 bit GPIO)</li><li>• 1 x (4 x RS-232/ 422/ 485, 2 x RS-232)</li><li>• 1 x power on/off button</li><li>• 9-32V Power input</li></ul> <p>Left Side</p> <ul style="list-style-type: none"><li>• 4 x Antenna holes (Left Side)</li></ul>
<b>U6-563</b>	<p>U6-500 Fanless Box PC</p> <p>CPU: Intel® Core™ i3-6100U (2x 2.3GHz, 3MB L2Cache, 15W)</p> <p>Memory: DDR4 2x SODIMM</p> <p>Front Side</p> <ul style="list-style-type: none"><li>• 1 x HDMI</li><li>• 1 x Display Port</li><li>• 1 x VGA</li><li>• 4 x USB 3.0/2.0</li><li>• 6 x 10/100/1000Mbps Ethernet</li><li>• 1 x GPIO (4/4bit)</li></ul> <p>Rear Side</p> <ul style="list-style-type: none"><li>• 1 x Audio (Line-out/ MIC-in)</li><li>• 1 x VHDCI (8 bit GPIO)</li><li>• 1 x (4 x RS-232/ 422/ 485, 2 x RS-232)</li><li>• 1 x power on/off button</li><li>• 9-32V Power input</li></ul> <p>Left Side</p> <ul style="list-style-type: none"><li>• 4 x Antenna holes (Left Side)</li></ul>

## Headquarter

10F-3, No.270, Sec.4,  
Chung Hsiao E. Rd.,  
Taipei, 10694, Taiwan

T +886 2 2751-7192  
E-mail: info@efco.com.tw

## EMEA

T +49-991-2009298-0  
E-mail: info@efcotec.com

## America

T +1-760-827-8600  
E-mail: sales-us@efcotec.com

# SmartMOD

Model	Description
<b>U6-565</b>	<p>U6-500 Fanless Box PC</p> <p>CPU: Intel® Core™ i5-6300U (2x 2.4/3.0GHz, 3MB L2Cache, 15W)</p> <p>Memory: DDR4 2x SODIMM</p> <p>Front Side</p> <ul style="list-style-type: none"><li>• 1 x HDMI</li><li>• 1 x Display Port</li><li>• 1 x VGA</li><li>• 4 x USB 3.0/2.0</li><li>• 6 x 10/100/1000Mbps Ethernet</li><li>• 1 x GPIO (4/4bit)</li></ul> <p>Rear Side</p> <ul style="list-style-type: none"><li>• 1 x Audio (Line-out/ MIC-in)</li><li>• 1 x VHDCI (8 bit GPIO)</li><li>• 1 x (4 x RS-232/ 422/ 485, 2 x RS-232)</li><li>• 1 x power on/off button</li><li>• 9-32V Power input</li></ul> <p>Left Side</p> <ul style="list-style-type: none"><li>• 4 x Antenna holes (Left Side)</li></ul>
<b>U6-567</b>	<p>U6-500 Fanless Box PC</p> <p>CPU: Intel® Core™ i7-6600U (2x 2.6/3.4GHz, 4MB L2Cache, 15W)</p> <p>Memory: DDR4 2x SODIMM</p> <p>Front Side</p> <ul style="list-style-type: none"><li>• 1 x HDMI</li><li>• 1 x Display Port</li><li>• 1 x VGA</li><li>• 4 x USB 3.0/2.0</li><li>• 6 x 10/100/1000Mbps Ethernet</li><li>• 1 x GPIO (4/4bit)</li></ul> <p>Rear Side</p> <ul style="list-style-type: none"><li>• 1 x Audio (Line-out/ MIC-in)</li><li>• 1 x VHDCI (8 bit GPIO)</li><li>• 1 x (4 x RS-232/ 422/ 485, 2 x RS-232)</li><li>• 1 x power on/off button</li><li>• 9-32V Power input</li></ul> <p>Left Side</p> <ul style="list-style-type: none"><li>• 4 x Antenna holes (Left Side)</li></ul>

## Headquarter

10F-3, No. 270, Sec. 4,  
Chung Hsiao E. Rd.,  
Taipei, 10694, Taiwan

T +886 2 2751-7192  
E-mail: info@efco.com.tw

## EMEA

T +49-991-2009298-0  
E-mail: info@efcotec.com

## America

T +1-760-827-8600  
E-mail: sales-us@efcotec.com



# SmartMOD

Model	Description
<b>UP6-561</b>	<p>UP6-500 Fanless Box PC</p> <p>CPU: Intel® Celeron® 3955U (2x 2.0GHz, 2MB L2Cache, 15W)</p> <p>Memory: DDR4 2x SODIMM</p> <p>Front Side</p> <ul style="list-style-type: none"><li>• 1 x HDMI</li><li>• 1 x Display Port</li><li>• 1 x VGA</li><li>• 4 x USB 3.0/2.0</li><li>• 2 x 10/100/1000Mbps Ethernet</li><li>• 4 x 10/100/1000Mbps Ethernet (w/POE)</li><li>• 1 x GPIO (4/4bit)</li></ul> <p>Rear Side</p> <ul style="list-style-type: none"><li>• 1 x Audio (Line-out/ MIC-in)</li><li>• 1 x VHDCI (8 bit GPIO)</li><li>• 1 x (4 x RS-232/ 422/ 485, 2 x RS-232)</li><li>• 1 x power on/off button</li><li>• 9-32V Power input</li></ul> <p>Left Side</p> <ul style="list-style-type: none"><li>• 4 x Antenna holes (Left Side)</li></ul>
<b>UP6-563</b>	<p>UP6-500 Fanless Box PC</p> <p>CPU: Intel® Core™ i3-6100U (2x 2.3GHz, 3MB L2Cache, 15W)</p> <p>Memory: DDR4 2x SODIMM</p> <p>Front Side</p> <ul style="list-style-type: none"><li>• 1 x HDMI</li><li>• 1 x Display Port</li><li>• 1 x VGA</li><li>• 4 x USB 3.0/2.0</li><li>• 2 x 10/100/1000Mbps Ethernet</li><li>• 4 x 10/100/1000Mbps Ethernet (w/POE)</li><li>• 1 x GPIO (4/4bit)</li></ul> <p>Rear Side</p> <ul style="list-style-type: none"><li>• 1 x Audio (Line-out/ MIC-in)</li><li>• 1 x VHDCI (8 bit GPIO)</li><li>• 1 x (4 x RS-232/ 422/ 485, 2 x RS-232)</li><li>• 1 x power on/off button</li><li>• 9-32V Power input</li></ul> <p>Left Side</p> <ul style="list-style-type: none"><li>• 4 x Antenna holes (Left Side)</li></ul>

## Headquarter

10F-3, No.270, Sec.4,  
Chung Hsiao E. Rd.,  
Taipei, 10694, Taiwan

T +886 2 2751-7192  
E-mail: info@efco.com.tw

## EMEA

T +49-991-2009298-0  
E-mail: info@efcotec.com

## America

T +1-760-827-8600  
E-mail: sales-us@efcotec.com



# SmartMOD

Model	Description
<b>UP6-565</b>	<p>UP6-500 Fanless Box PC</p> <p>CPU: Intel® Core™ i5-6300U (2x 2.4/3.0GHz, 3MB L2Cache, 15W)</p> <p>Memory: DDR4 2x SODIMM</p> <p>Front Side</p> <ul style="list-style-type: none"><li>• 1 x HDMI</li><li>• 1 x Display Port</li><li>• 1 x VGA</li><li>• 4 x USB 3.0/2.0</li><li>• 2 x 10/100/1000Mbps Ethernet</li><li>• 4 x 10/100/1000Mbps Ethernet (w/POE)</li><li>• 1 x GPIO (4/4bit)</li></ul> <p>Rear Side</p> <ul style="list-style-type: none"><li>• 1 x Audio (Line-out/ MIC-in)</li><li>• 1 x VHDCI (8 bit GPIO)</li><li>• 1 x (4 x RS-232/ 422/ 485, 2 x RS-232)</li><li>• 1 x power on/off button</li><li>• 9-32V Power input</li></ul> <p>Left Side</p> <ul style="list-style-type: none"><li>• 4 x Antenna holes (Left Side)</li></ul>
<b>UP6-567</b>	<p>UP6-500 Fanless Box PC</p> <p>CPU: Intel® Core™ i7-6600U (2x 2.6/3.4GHz, 4MB L2Cache, 15W)</p> <p>Memory: DDR4 2x SODIMM</p> <p>Front Side</p> <ul style="list-style-type: none"><li>• 1 x HDMI</li><li>• 1 x Display Port</li><li>• 1 x VGA</li><li>• 4 x USB 3.0/2.0</li><li>• 2 x 10/100/1000Mbps Ethernet</li><li>• 4 x 10/100/1000Mbps Ethernet (w/POE)</li><li>• 1 x GPIO (4/4bit)</li></ul> <p>Rear Side</p> <ul style="list-style-type: none"><li>• 1 x Audio (Line-out/ MIC-in)</li><li>• 1 x VHDCI (8 bit GPIO)</li><li>• 1 x (4 x RS-232/ 422/ 485, 2 x RS-232)</li><li>• 1 x power on/off button</li><li>• 9-32V Power input</li></ul> <p>Left Side</p> <ul style="list-style-type: none"><li>• 4 x Antenna holes (Left Side)</li></ul>

## Headquarter

10F-3, No. 270, Sec. 4,  
Chung Hsiao E. Rd.,  
Taipei, 10694, Taiwan

T +886 2 2751-7192  
E-mail: info@efco.com.tw

## EMEA

T +49-991-2009298-0  
E-mail: info@efcotec.com

## America

T +1-760-827-8600  
E-mail: sales-us@efcotec.com



Note : All product specifications are subject to change without notice